

231 LED Installation Beacon

Technical specifications

Dimensions (Diameter x Height):	28.7 mm x 46 mm
Dome:	PC, transparent
Fixing :	Installation mounting for Ø 22,5 mm (M 22 x 1,5 mm)
Housing :	PC/ABS-Blend
Connection:	2 wires, c. 105 mm long
Operating voltage:	24 V =, 115 V ~, 230 V ~
Current consumption:	80 mA at 12 V 45 mA at 24 V 15 mA at 115 V 20 mA at 230 V
Starting current:	< 0,5 A at 24 V
Life duration:	up to 100.000 h
Others :	Nut and seal included in assembly

Technical Diagrams

231 LED Installation Beacon

